## **SIEMENS**

## Data sheet

## 6ES7131-6TF00-0CA0

SIMATIC ET 200SP, digital input module, DI 8x NAMUR High Feature, suitable for BU type A0, Color code CC01, channel diagnostics



General information	
Product type designation	DI 8xNAMUR HF
HW functional status	from FS04
Firmware version	
<ul> <li>FW update possible</li> </ul>	Yes
usable BaseUnits	BU type A0
Color code for module-specific color identification	CC01
plate	
Product function	
● I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated as of</li> </ul>	V13 / V13
version	
<ul> <li>STEP 7 configurable/integrated as of version</li> </ul>	V5.5 SP3 / -
<ul> <li>PROFIBUS as of GSD version/GSD revision</li> </ul>	GSD Revision 5
<ul> <li>PROFINET as of GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
• DI	Yes

Counter	No
Oversampling	No
• MSI	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Encoder supply	
Number of outputs	8
Short-circuit protection	Yes
24 V encoder supply	
• 24 V	No
<ul> <li>Short-circuit protection</li> </ul>	No
Power loss	
Power loss, typ.	1.5 W
Address area	
Address space per module	1 huter 1 1 hute for Ol information
<ul> <li>Address space per module, max.</li> </ul>	1 byte; + 1 byte for QI information
Hardware configuration	
Selection of BaseUnit for connection variants	
• 1-wire connection	BU type A0
	BU type A0 BU type A0
• 1-wire connection	
<ul><li> 1-wire connection</li><li> 2-wire connection</li></ul>	BU type A0
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul>	BU type A0 BU type A0 + external terminals
<ul><li> 1-wire connection</li><li> 2-wire connection</li><li> 3-wire connection</li></ul>	BU type A0 BU type A0 + external terminals
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs	BU type A0 BU type A0 + external terminals BU type A0 + external terminals
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs	BU type A0 BU type A0 + external terminals BU type A0 + external terminals
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable	BU type A0 BU type A0 + external terminals BU type A0 + external terminals 8; NAMUR Yes
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension	BU type A0 BU type A0 + external terminals BU type A0 + external terminals 8; NAMUR Yes Yes; 0.5 s, 1 s, 2 s
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation	BU type A0 BU type A0 + external terminals BU type A0 + external terminals BU type A0 + external terminals 8; NAMUR Yes Yes; 0.5 s, 1 s, 2 s Yes; rising edge, falling edge, edge change
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         Structure         Structure         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; rising edge, falling edge, edge change         Yes; 2 to 32 signal changes
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         Structure         Structure         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; rising edge, falling edge, edge change         Yes; 2 to 32 signal changes
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window Input voltage	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         State         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; 7 to 32 signal changes         Yes; 0.5 s, 1 s to 100 s in 1-s steps
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window Input voltage <ul> <li>Rated value (DC)</li> </ul>	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         State         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; 7 to 32 signal changes         Yes; 0.5 s, 1 s to 100 s in 1-s steps
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window Input voltage <ul> <li>Rated value (DC)</li> <li>Input current</li> </ul>	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         State         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; 7 to 32 signal changes         Yes; 0.5 s, 1 s to 100 s in 1-s steps
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window Input voltage <ul> <li>Rated value (DC)</li> <li>Input current</li> <li>for 10 k switched contact</li> </ul>	BU type A0 BU type A0 + external terminals BU type A0 + external terminals BU type A0 + external terminals 8; NAMUR Yes Yes; 0.5 s, 1 s, 2 s Yes; 0.5 s, 1 s, 2 s Yes; rising edge, falling edge, edge change Yes; 2 to 32 signal changes Yes; 0.5 s, 1 s to 100 s in 1-s steps 8.2 V
<ul> <li>1-wire connection</li> <li>2-wire connection</li> <li>3-wire connection</li> <li>4-wire connection</li> </ul> Digital inputs Number of digital inputs Digital inputs, parameterizable Pulse extension Edge evaluation Signal change flutter Flutter observation window Input voltage <ul> <li>Rated value (DC)</li> <li>Input current</li> <li>for 10 k switched contact</li> <li>— for signal "0"</li> </ul>	BU type A0         BU type A0 + external terminals         BU type A0 + external terminals         BU type A0 + external terminals         Ves         Yes         Yes; 0.5 s, 1 s, 2 s         Yes; rising edge, falling edge, edge change         Yes; 2 to 32 signal changes         Yes; 0.5 s, 1 s to 100 s in 1-s steps         8.2 V         0.35 to 1.2 mA

— for signal "0", max. (permissible quiescent current)	0.5 mA
— for signal "1"	typ. 8 mA
for NAMUR encoders	
— for signal "0"	0.35 to 1.2 mA
— for signal "1"	2.1 to 7 mA
Input delay (for rated value of input voltage)	
<ul> <li>tolerated changeover time for changeover contacts</li> </ul>	300 ms
for standard inputs	
— parameterizable	No
for NAMUR inputs	
— at "0" to "1", max.	12 ms
— at "1" to "0", max.	12 ms
Cable length	
● shielded, max.	200 m
Encoder	
Connectable encoders	
<ul> <li>NAMUR encoder/changeover contact according to EN 60947</li> </ul>	Yes
<ul> <li>Single contact / changeover contact unconnected</li> </ul>	Yes
• Single contact / changeover contact connected with 10 $k\Omega$	Yes
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes; channel by channel
Hardware interrupt	Yes; Parameterizable, channels 0 to 7
Diagnostic messages	
<ul> <li>Diagnostic information readable</li> </ul>	Yes
<ul> <li>Monitoring the supply voltage</li> </ul>	Yes
— parameterizable	Yes
<ul> <li>Monitoring of encoder power supply</li> </ul>	No
• Wire-break	Yes; channel by channel
Short-circuit	Yes; channel by channel
Diagnostics indication LED	
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green PWR LED
<ul> <li>Channel status display</li> </ul>	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	Yes; red LED
• for module diagnostics	Yes; green/red DIAG LED

Potential separation	
Potential separation channels	
• between the channels	No
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
• between the channels and the power supply of the electronics	Yes
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for safety functions	No
Ambient conditions	
Ambient temperature during operation	
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
<ul> <li>vertical installation, min.</li> </ul>	-30 °C
<ul> <li>vertical installation, max.</li> </ul>	50 °C
Altitude during operation relating to sea level	
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	32 g
last modified:	05/09/2020