AL112NX Alarm Sounder & Xenon Beacon

The AL112NX features the 119dB(A) A112N alarm sounder combined with the L101X Xenon beacon. The compact, robust housing is ideal for all general signalling applications including fire, security and process control.

The 5 Joule Xenon strobe generates over 200 candela of light output. DC versions have multile flash rates selectable udring installation. Sounder & beacon may be connected from a single supply for simultaneous operation or from separate supplies for independent operation.

Tone table:

ione table	e:		
Stage 1	Frequency Description.	Stage 2	Stage 3
Tone 1	340 Hz Continuous	Tone 2	Tone 5
Tone 2	800/1000Hz @ 0.25 sec Alternating	Tone 17	Tone 5
Tone 3	500/1200Hz @ 0.3Hz 0.5 sec Slow Whoop	Tone 2	Tone 5
Tone 4	800/1000Hz @ 1Hz Sweeping	Tone 6	Tone 5
Tone 5	2400Hz Continuous	Tone 3	Tone 20
Tone 6	2400/2900Hz @ 7Hz Sweeping	Tone 7	Tone 5
Tone 7	2400/2900Hz @ 1Hz Sweeping	Tone 10	Tone 5
Tone 8	500/1200/500Hz @ 0.3Hz Sweeping	Tone 2	Tone 5
Tone 9	1200/500Hz @ 1Hz - DIN / PFEER P.T.A.P.	Tone 15	Tone 2
Tone 10	2400/2900Hz @ 2Hz Alternating	Tone 7	Tone 5
Tone 11	1000Hz @ 1Hz Intermittent	Tone 2	Tone 5
Tone 12	800/1000Hz @ 0.875Hz Alternating	Tone 4	Tone 5
Tone 13	2400Hz @ 1Hz Intermittent	Tone 15	Tone 5
Tone 14	800Hz 0.25sec on, 1 sec off Intermittent	Tone 4	Tone 5
Tone 15	800Hz Continuous	Tone 2	Tone 5
Tone 16	660Hz 150mS on, 150mS off Intermittent	Tone 18	Tone 5
Tone 17	544Hz (100mS)/440Hz (400mS) - NF S 32-001	Tone 2	Tone 27
Tone 18	660Hz 1.8sec on, 1.8sec off Intermittent	Tone 2	Tone 5
Tone 19	1.4KHz-1.6KHz 1s, 1.6KHz-1.4KHz 0.5s -NFC48-265	Tone 2	Tone 5
Tone 20	660Hz Continuous	Tone 2	Tone 5
Tone 21	554Hz/440Hz @ 1Hz Alternating	Tone 2	Tone 5
Tone 22	544Hz @ 0.875 sec. Intermittent	Tone 2	Tone 5
Tone 23	800Hz @ 2Hz Intermittent	Tone 6	Tone 5
Tone 24	800/1000Hz @ 50Hz Sweeping	Tone 29	Tone 5
Tone 25	2400/2900Hz @ 50Hz Sweeping	Tone 29	Tone 5
Tone 26	Bell	Tone 2	Tone 15
Tone 27	554Hz Continuous	Tone 26	Tone 5
Tone 28	440Hz Continuous	Tone 2	Tone 5
Tone 29	800/1000Hz @ 7Hz Sweeping	Tone 7	Tone 5
Tone 30	300Hz Continuous	Tone 2	Tone 5
Tone 31	660/1200Hz @ 1Hz Sweeping	Tone 26	Tone 5
Tone 32	Two tone chime.	Tone 26	Tone 15
Tone 33	745Hz @ 1Hz Intermittent	Tone 2	Tone 5
Tone 34	1000 & 2000Hz @ 0.5 sec Alternating - Singapore	Tone 38	Tone 45
Tone 35	420Hz @ 0.625 sec Australian Alert	Tone 36	Tone 5
Tone 36	500-1200Hz 3.75sec / 0.25sec. Australian Evac.	Tone 35	Tone 5
Tone 37	1000Hz Continuous - PFEER Toxic Gas	Tone 9	Tone 45
Tone 38	2000Hz Continuous	Tone 34	Tone 45
Tone 39	800Hz 0.25sec on, 1 sec off Intermittent	Tone 23	Tone 17
Tone 40	544Hz (100mS)/440Hz (400mS) - NF S 32-001	Tone 31	Tone 27
Tone 41	Motor Siren - slow rise to 1200 Hz	Tone 2	Tone 5
Tone 42	Motor Siren - slow rise to 800 Hz	Tone 2	Tone 5
Tone 43	1200 Hz Continuous	Tone 2	Tone 5
Tone 44	Motor Siren - slow rise to 2400 Hz	Tone 2	Tone 5
Tone 45	1KHz 1s on, 1s off Intermittent - PFEER Gen. Alarm	Tone 38	Tone 34

Country specific or custom tone configurations and alarm frequencies are available upon request.

Specification:

Sounder:		
Maximum output:	119dB(A) @ 1 metre	
Nominal output:	112dB(A) @ 1m +/- 3dB - Tone 2	
No. of tones:	45 (UKOOA / PFEER compliant)	
No. of stages:	3	
Volume control:	Max. 112dB(A); Min. 100dB(A) - Tone 2	
Effective range:	125m @ 1KHz	
Voltages DC:	24V dc (10-30V dc); 48V dc (35-60V dc)	
[DC units can use 2	4V ac for single stage applications.]	
Voltages AC:	AC: 24V ac; 115V ac; 230V ac	
Stage switching:	Negative Reverse polarity stage switching on DC units.	
Beacon:		
Energy:	5 Joules (5Ws)	
Flash rate:	1Hz (60 fpm)	
Peak Candela:	500,000 cd - calc. from energy (J)	
Effective candela:	250 cd - calc. from energy (J)	
Peak candela:	86,935 cd* - measured ref. to I.E.S.	
Effective candela:	200 cd* - measured ref. to I.E.S.	
Lens colours:	Amber, Blue, Clear, Green, Magenta, Red & Yellow	
Tube life:	Emissions are reduced to 70% after 8 million flashes	
General:		
Ingress protection:	IP66	
Housing material:	High impact UL94 VO & 5VA FR ABS	

Weight: DC: 2.00kg AC:2.30kg

*Candela measurements representative of performance with clear lens at optimum voltage.

*SPL data +/-3dB(A). Measured at optimum voltage.

2 x M20 clearance gland entries in side & back

Red (RAL3000)

-25 to +55°C

-40 to +70°C

90% at 20°C.

0.5 to 4.0mm² cables.

Colour:


Cable entries:

Operating temp:

Relative humidity:

Storage temp:

Terminals:





Version:	Part code:
12V dc	AL112NXDC012[x]/[y]
24V dc	AL112NXDC024[x]/[y]
48V dc	AL112NXDC048[x]/[y]
24V ac	AL112NXAC024[x]/[y]
115V ac	AL112NXAC115[x]/[y]
230V ac	AL112NXAC230[x]/[y]
[x] = Housing colour:	R: Red, G: Grey
[y] = Lens colour:	A: Amber, B: Blue. C: Clear, G: Green, M: Magenta R: Red, Y: Yellow

Suffix part number with '-P' for programmable, 4 stage, 45 tone version. Suffix part number with '-F' for forward facing Xenon beacon. Suffix part number with '-UL' for UL approved version.

Alarm sounder:

Version:		Voltage:	Current:
12/24V dc		10-30V dc	200mA*
48V dc		35-60V dc	120mA*
24V ac	50/60Hz	+/-10%	500mA
115V ac	50/60Hz	+/-10%	100mA
230V ac	50/60Hz	+/-10%	60mA

* current at nominal voltage on Tone 2

Xenon beacon:

Version:		Voltage:	Current:
12V dc		10-14V dc	500mA
24V dc		20-28V dc	250mA
48V dc		42-54V dc	175mA
24V ac	50/60Hz	+/-10%	300mA
115V ac	50/60Hz	+/-10%	70mA
230V ac	50/60Hz	+/-10%	35mA

Features:

- Automatic synchronisation on multi-sounder system.
- High output Xenon beacon
- DC voltage units feature multiple flash rates.
- Continuously rated.
- Stainless steel fixings.
 - Unit can be mounted using external lugs or internal BESA compatible fixing positions.
- Duplicate cable terminations (in & out for daisy-chain installations).
- Tropicalisation available on request.
- Available with custom tone configurations and frequencies.
- 'Programmable' version available:
- 45 alarm tones
- 4 remotely selectable stages
- Any tone can be assigned to any stage
- User configurable continuous frequency tone

Approvals

- A112N alarm sounder is VdS approved to EN54-3 (CPD 89/106/EEC).
- Xenon beacon (L101X) VdS approved to EN54-23:2010 (CPD 89/106/EEC).
- UKOOA/PFEER compliant alarm tones.
- UL approved version available.
- GOST-R approved. Cert: POCC GB-JB05-H0014







