## **SIEMENS**

Data sheet 7KT1661

SENTRON, measuring device, 7KT PAC1600, LCD, L-L: 400 V, L-N: 230 V, 5 A, strd rail instr., 3-phase, Modbus RTU/ASCII, apparent/active/ reactive energy, self-powered, screw terminals



SENTRON
basic
Measuring instrument
complete

General technical data		
Operating mode for measured value detection		
<ul> <li>automatic line frequency detection</li> </ul>	Yes	
• set at 50 Hz	No	
• set to 60 Hz	No	
Voltage curve	Sinusoidal or distorted	
Measurable line frequency / initial value	45 Hz	
Measurable line frequency / Full-scale value	66 Hz	
Measuring procedure / for voltage measurement	TRMS	

Supply voltage	
Type of voltage / of the supply voltage	self-powered
Consumed active power	
<ul><li>without expansion module / typical</li></ul>	1.6 W

Protection class	
Protection class IP	
• on the front	IP40
Rear side	IP20
Electricity  Measurable current / 2 / at AC / Rated value	5 A
ivieasurable current / 2 / at AC / Rated value	5 A
Suitability	
Suitability for operation	Standard mounting rail device
Product function	
Product function	
• reactive power measurement	Yes
• frequency measurement	Yes
voltage measurement	Yes
Current measurement	Yes
active power measurement	Yes
Display and an aution	
Display and operation  Design of the display	LCD
Number of keys	3
Communication	
Transfer rate	4 000 11 77
• minimum	1 200 kbit/s
• maximum	115 200 kbit/s
Inputs Outputs	
Input voltage / at digital input	
<ul><li>initial value for signal&lt;1&gt;-recognition</li></ul>	85 V
• at DC / maximum	240 V
<ul><li>Full-scale value for signal&lt;0&gt; recognition</li></ul>	240 V
Number of digital outputs	0
Number of digital inputs	1
Type of switching output	solid state
Type of electrical connection	
at the digital outputs	screw-type terminals
Operating conditions for digital inputs / external	Yes
voltage supply	
Measuring inputs	
Measurable supply voltage	
<ul><li>between (PE)N and L / at AC / minimum</li></ul>	187 V
<ul><li>between (PE)N and L / at AC / maximum</li></ul>	264 V
<ul> <li>between (PE)N and L / at AC / maximum rated</li> </ul>	230 V
value	

<ul> <li>between the outer conductors / at AC / maximum rated value</li> </ul>	400 V
Measuring category / for voltage measurement	CATIII
Continuous current / at AC / maximum permissible	6 A
Measuring category / for current measurement	CATIII
Zero-point suppression / for current measurement	10 mA
Relative measurable current / at AC	
• minimum	1 %
• maximum	120 %
Apparent power consumption / for current measurement	
<ul><li>with measuring range 5 A / per phase</li></ul>	3 V·A
Measuring procedure / for current measurement	TRMS
Measurable current / 1 / at AC / Rated value	5 A
Connections	
Type of electrical connection	
<ul> <li>at the measurement inputs for voltage</li> </ul>	screw-type terminals
<ul> <li>at the measurement inputs for current</li> </ul>	screw-type terminals
Mechanical Design	
Height	90 mm
Width	71.6 mm
Depth	63 mm
Mounting position	any
Mounting type / panel mounting	No
Net weight	280 g
Environmental conditions	
Degree of pollution	2
Installation altitude / at height above sea level / maximum	2 000 m
Relative humidity / at 25 °C / without condensation /	
Relative humidity / at 25 °C / without condensation / during operation	
	80 %
during operation	80 %
during operation  • maximum	80 % -25 °C
during operation  • maximum  Ambient temperature	

Certificates

Certificate of suitability

Approval Russia

• during storage / minimum

• during storage / maximum

-25 °C

70 °C

## **Declaration of Conformity**



## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/lowvoltage/catalogs

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=7KT1661

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/7KT1661

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax\_en.aspx?mlfb=7KT1661

**CAx-Online-Generator** 

http://www.siemens.com/cax

**Tender specifications** 

http://www.siemens.com/specifications